

#### **FEATURES**

- Positive-locking spring loaded stainless steel latches and a one piece neoprene gasket provide a watertight seal.
- Shoc♦Loc™ bi-pin spring loaded lampholders for double ended lamps provide a positive contact and resistance to shock and vibration while maintaining positive electrical pin contact. Standard for T5, T8 and T12 lamp types.
- Available in one, two and three lamp units.
- Supplied in 120v 60Hz HPF as standard. Other options in 220v 50Hz, 220v 60Hz and 277v 60Hz also available.
- Available in 17w, 18w, 20w, 24w, 32w, 35w, 36w, 40w, 44w, 54w and 60w fluorescent.
- Adjustable mounting brackets allow a 110° range of mounting positions.
- Low temperature rated ballast 0° F (-18° C) standard on T5 and T8; T12 HO linear fluorescents -20° F (-29° C).
- Emergency versions available.
- 5 year warranty.

## **DIMENSIONS** 1/32 MNTG. HOLES 11 1/2 WALL MOUNT (LL OPTION) 9 3/4 O) Mounts Standard 6 <sup>7</sup>/<sub>8</sub> Surface (option SF) 5 3/ D 31 <sup>1</sup>/<sub>2</sub> 55 <sup>1</sup>/<sub>2</sub> 30 <sup>1</sup>/<sub>4</sub> 54 <sup>1</sup>/<sub>4</sub> 29 <sup>1</sup>/<sub>4</sub> 25 <sup>7</sup>/<sub>5</sub> 36 17W, 18W, 20W, 24W, 35W 32W, 36W, 40W, 44W, 54W, 60W

#### **APPROVALS**

- UL 844 Hazardous Location Class I Division 2 Groups A, B, C and D Class I Zone 2 Groups IIA, IIB, IIB+ H2 and IIC
- UL 924 Emergency Lighting Equipment
- UL 1598A Marine Outside Type Saltwater
- Class I Division 2, Groups A, B, C and D Class II Division I, Groups E, F and G Class III
- **IP 66**
- Type 4X
- **ABS**

#### **APPLICATIONS**

- **Hazardous Locations**
- Marine and wet environments
- Offshore oil and gas exploration and production
- Salt and potash mines
- Water treatment facilities
- Industrial wash pits
- Salt and potash mines
- Petrochemical

#### **OPTIONS**

To obtain a luminaire with any of the options listed below, please add the following suffix to the part number (not all options can be combined):

•	Type 316 Stainless Steel Housing	/316
$\blacksquare$	Terminal Block	Т
$\blacksquare$	Shock Mount	SM
$\blacksquare$	Surface Mount	SF
$\blacksquare$	Wall Mount	LL
$\blacksquare$	Pendant Mount 3/4" NPT	PT
$\blacksquare$	Fused Ballast (not for marine use)	F
$\blacksquare$	Tempered Glass Lens	TG
$\blacksquare$	Dual Safety Cable Attachment Points	W
$\blacksquare$	Emergency Ballast (1 lamp)	EM*
$\blacksquare$	Emergency Ballast (2 lamps)	EM2**
$\blacksquare$	120-277 50/60Hz (17, 24, 32, 35, 54 & 60w)	-127
$\blacksquare$	220VAC 50Hz	-225
$\blacksquare$	220VAC 60Hz	-226
$\blacksquare$	277VAC 60Hz	-276

- \* 24w or 54w Marine Only.
- \*\* Not available in 24w, 35w, 54w or 60w.

© Copyright 2006. Not to be reproduced without express permission of Pauluhn Electric Manufacturing, LLP

# HAZARDOUS LOCATIONS CLASS I DIVISION 2 OUTSIDE TYPE SALTWATER MARINE STAINLESS STEEL AND ALUMINUM FLUORESCENT LUMINAIRES WITH FLAT LENS



#### **LUMINAIRE TECHNICAL SPECIFICATIONS**

#### **HOUSINGS**

Available in type 304 stainless steel with a natural finish and stainless steel mounting fittings or in copper free aluminum with an oven-cured polyester powder coat protective finish and aluminum mounting fittings with a natural finish.

#### **LENS FRAME AND LATCHES**

Stainless steel for all types.

#### **LENS**

Polycarbonate flat lens as standard.

#### **REFLECTOR**

White high gloss powder coated aluminum.

#### **LAMPHOLDERS**

Shoc♦Loc™ bi-pin spring loaded lampholders for double ended lamps provide a positive contact and resistance to shock and vibration while maintaining positive electrical pin contact. Standard for T5, T8 and T12 lamp types.



#### **MOUNTINGS**

Through (4) Ø  $^{11}\!/_{32}$  " or (2) Ø  $^{7}\!/_{16}$  " mounting holes provided on the adjustable brackets.

#### **GASKETS**

One piece neoprene gasket provides a watertight seal between the lens and housing.

#### LAMP TYPE

All luminaires supplied with lamps.

#### BALLAST

A High Power Factor (HPF) 120v 60Hz ballast is supplied as standard. 17w, 20w, 24w, 32w, 40w and 54w luminaires are rated for starting in temperatures down to -18°C (0°F). 35w, 44w (solid state) and 60w luminaires are rated for temperatures down to -29°C (-20°F). 18w and 36w are available in 230v 50Hz only. Other voltage options and emergency ballasts are available. All ballast electronic with the exception of 20w T12. Magnetic ballasts are available, please contact factory.

#### **OUTLETS**

35w, 44w, 60w

17w, 18w, 20w, 24w, 32w, 36w, 40w, 54w FX4008

All units are supplied with two  $^{3}/_{4}^{"}$  NPT outlets, one plugged, providing a thru-feed service where required.

#### **AMBIENT & OPERATING TEMPERATURE**

17,18, 20 & 32 watt are rated at 40/55° C with a temperature code of T5/T4A. The 35, 36, 40, 44 & 60 watt are rated 40° C, T3C, except the 3 lamp 35 & 60 watt luminaires are rated 25° C, T3C.

### ORDERING REFERENCES

					ORDERI	NG REF
	FL	UORES	CENT LUM	INAIR	S	
DESCRIPTION	NO OF LAMPS	LAMP TYPE	FWFN ALUM	WT (lbs)	FWFN SS	WT (lbs)
17w 263 MA 24" Lamp	One Two Three	F17T8	FWFN117A FWFN217A FWFN317A	14.1 14.4 17.2	FWFN117S FWFN217S FWFN317S	20.0 19.0 23.1
*18w 360 MA 24" Lamp	One Two Three	F18T8	FWFN118A FWFN218A FWFN318A	15.2 15.4 19.2	FWFN118S FWFN218S FWFN318S	21.0 21.3 25.1
20w Trigger Start 24" Lamp	One Two Three	F20T12	FWFN120A FWFN220A FWFN320A	14.0 15.5 19.4	FWFN120S FWFN220S FWFN320S	21.1 20.0 25.2
24w High Output	One Two Three	F24T5 /HO	FWFN124A FWFN224A FWFN324A	14.1 14.4 17.2	FWFN124S FWFN224S FWFN324S	20.0 20.3 23.1
32w 265 MA 48" Lamp	One Two Three	F32T8	FWFN132A FWFN232A FWFN332A		FWFN132S FWFN232S FWFN332S	30.6 31.0 34.1
35w High Output 800 MA 24" Lamp	One Two Three	F24T12	FWFN135A FWFN235A FWFN335A	12.4 12.6 8.4	FWFN135S FWFN235S N/A	26.2 26.0 N/A
*36w 440 MA 48" Lamp	One Two Three	F36T8	FWFN136A FWFN236A FWFN336A	21.3	FWFN136S FWFN236S FWFN336S	31.6 32.1 36.1
40w 430 MA 48" Lamp	One Two Three	F40T12	FWN140A FWN240A FWN340A	20.9 21.5 25.6	FWFN140S FWFN240S N/A	31.0 33.0 N/A
44w High Output 800 MA 48" Lamp	One Two Three	F48T8 /HO	FWFN144A FWFN244A FWFN344A	21.8	FWFN144S FWFN244S N/A	32.1 33.0 N/A
54w High Output	One Two Three	F54T5 /HO	FWFN154A FWFN254A FWFN354A	19.8 20.3 23.3	FWFN154S FWFN254S FWFN354S	30.6 31.1 34.1
60w High Output 800 MA 48" Lamp	One Two Three	F48T12 /HO	FWFN160A FWFN260A FWFN360A	23.3	FWFN160S FWFN260S N/A	33.3 36.3 N/A

_					
*	Available	in	230v	50Hz	only.

	SPAR	E PARTS	
BALLASTS 120	OV AC 60HZ	LAMPS	
1 x 17w	FX5173	17w	FX3528
2 x 17w	FX5260	18w	FX3562
1 x 20w	FX5058	20w	FX3506
2 x 20w	FX5032	24w	FX3568
1 x 24w	FX5307	32w	FX3527
2 x 24w	FX5307	35w	FX3507
1 x 32w	FX5173H	36w	FX3557
2 x 32w	FX5260H	40w	FX3504
1 x 35w	FX5100	44w	FX3565
2 x 35w	FX5027	54w	FX6567
1 x 40w	FX5054	60w	FX3505
2 x 40w	FX5010		
1 x 44w	FX5287		
2 x 44w	FX5287	GASKETS	
1 x 54w	FX5305	29 1/4"	GKT6088-69.5
2 x 54W	FX5305	53 1/4"	GKT6088-117.5
1 x 60w	FX5044		
2 x 60w	FX5027	MOUNTS	
		Wall	FX7031S/A
230V AC 50HZ		1	FX7027S/A
1 x 18w	FX5237	Surface	FX7022S/A
2 x 18w	FX5239	Pipe Mount Kit	
1 x 36w	FX5238	Chain Mount Kit	FX7025
2 x 36w	FX5240	Chain Mount Kit Shock Mount	FX7004A
		BEAM CLAMP	KIT
FLAT LENS	=>/0.40.4	(Safety Cable &	Cord connector
29 1/4"	FX2134	1	FX7028
53 1/4"	FX2135		
EMERGENCY I			
120-277v AC	FX5128HDL	J	

FX4004

FX4005

FX4009